FZ100 User Guide V1.0

Revision Date: 4/21/2025



12822 Unison Rd Suite B Houston, https://falconzoom.com TX 77044 (737) 406 2009

info@falconzoom.com support@falconzoom.com



Contents

Contents	2
1 Copyright and Disclaimer	
2 Product Overview	
3 Product Functions	
4 Specifications	
5 Standard Package and Optional Accessories	
6 Appearance and Structure	
7. LED light Indicator	7
8. Initialize device via GPRS/SMS command	8
9 Installation	11
10 Warranty Terms	12
Contact Us	12



1 Copyright and Disclaimer

Copyright © 2025 Falcon Zoom. All rights reserved. Unauthorized reproduction, transfer, distribution, or storage of any part of this document without prior written permission from Falcon Zoom is strictly prohibited.

While this manual provides accurate information, ongoing research and development may result in periodic updates. The version you are reading reflects the current state of our products, and we have strived to present a clear and comprehensive description to facilitate ease of use. However, due to rapid technological advancements, some technical expressions may evolve. We reserve the right to make modifications and improvements without prior notice.

2 Product Overview

The FZ100 is a compact, one-time-use disposable GPS tracker designed for asset monitoring with LTE 4G connectivity.

Equipped with a high-capacity 4500mAh battery, it can operate for up to 10 years, with data uploads occurring every 5 days. The device supports multiple working modes and features an anti-removal alarm for enhanced security.

3 Product Functions

Items	Functions
Communication	Location Data transmitting-GPRS(TCP/UDP)
	Commands- GPRS/Serial port
Position Tracking	Real time location monitoring mode
	Track by time interval (range from 5mins to 30 days interval)
	Track by time point (1 to 24 time point one day)
	up to 3-10 years working
Alarm	Low battery alarm (GRPS)
	Speeding alarm (GPRS)
	Anti-dismantle alarm(GPRS)
Buffer	Data in Buffer when in GPRS blind area
Initialization	Initialize tracker's Parameters via GPRS/Serial port



4 Specifications

Items	Specifications			
Tracker Dimension	2.71 inches X 1.61 inches X 1.14 inches (69*41*29 mm)			
Tracker Color	Black (Other colors can be customized)			
Weight	Tracker weight	0.22 lbs	Total package	0.33 lbs
Working voltage	DC 3V			
Working current	40mA-100mA/3V			
Sleeping mode	<15uA			
Working Days	Once a day location update, battery will last for 3 years. One location update every 5 days, battery will last for 10 years.			
Built-in battery	Li-MnO2 disposable battery 4500mAh 3pc 123A			
Operating temperature	-13°F to 176°F.			
Operating humidity	0% 100%			
LED indicator	Green led and Red led light indicates GPS and GSM status respectively			
Power Switch	Built-in battery switch on Mainboard			
Light Sensor	Built-in light sensor for tamper alert			
Magnet	With 5pcs strong magnet (Optional)			
4G LTE Module	SIMCOM 7670SA 4G CAT1 Cellular Module 4G LTE FDD: B1/B2/B3/B4/B5/B7/B8/B28/B66 2G GSM/GPRS/EDGE: 850/900/1800/1900MHz			
	Positioning accuracy	<= 2m CEP		
	Cold start time	<=30s(AGNSS Close) <=5.5s(AGNSS Open)		
GPS Module	Warm start time	<= 2s (in average)		
	GPS Sensitivity	-159Db		
	GPS L1 C/A	1575.42 MHz		
	GLONASS L1	1602.5625 MHz		
	BeiDou B1	1561.098 MHz		
	QZSS L1	1575.42 MHz		

5 Standard Package and Optional Accessories

Name	Picture	Standard/Optional Parts
FZ100 Tracker		Standard
Magnet		Optional
Mirco-USB Configuration cable		Optional

6 Appearance and Structure










7. LED light Indicator

LEC	Light	ON/OFF Indication		Description	
		Light On	Light Off	Description	
			Off	Power Off	
		Always on		The firmware working, but the	
GSM	Green			SIM card cannot be recognized	
		Blinking every 0.1 sec		Searching for Cellular Network	
				or connecting to the platform	
		Blinking every 1 sec		Online	
GPS	Red		Off	GPS closed or GPS no data	
		Blinking every 0.1sec		Searching GPS signal	
		Blinking every 1 sec		GPS valid, Position get fixed	

9 Installation

Install the device in car//Trailer.







10 Warranty

- The warranty period is **12 months** from the delivery date. However, it does not cover defects, failures, or damages caused by **improper use**, **unauthorized disassembly**, **or modifications**.
- Our obligations are limited to repairing the defect, replacing the faulty part, or, at our discretion, replacing the product entirely.
- Repairs or replacements under this warranty do not entitle the user to an extension or renewal of the warranty period.
- The warranty applies **only to defects in materials, design, and workmanship** and does not cover other issues.

Contact Us

12822 Unison Rd Suite B Houston, TX 77044 (737) 406 2009 https://falconzoom.com info@falconzoom.com support@falconzoom.com